

YSOFT SAFEQ TERMINAL ULTRALIGHT



COMPACT, FAST WAY TO AUTHENTICATE USERS FOR PRINTER ACCESS

The YSoft SAFEQ Terminal UltraLight offers a fast and easy way for users to authenticate at multifunction devices (MFDs) or networked printers. Its compact size packs a lot of power. Users can enter a PIN on the keypad and/or swipe an ID card.

HIGHLIGHTS INCLUDE

- Soft-touch keypad doesn't require a firm press and can optionally be configured to beep to indicate a touch has been registered
- Status LED indicates if login was unsuccessful
- Automatic logout locks the printer after use (time defined by the print administrator)
- One button prints all waiting print jobs; UltraLight Print Only prints automatically upon login

Y Soft designs, tests and manufactures the YSoft SAFEQ Terminal UltraLight models in the European Union and provides global certifications and logistics through warehouses located in the Czech Republic, USA, China, Australia and Singapore.



THE TERMINAL ULTRALIGHT COMES IN TWO MODELS:

- YSoft SAFEQ Terminal UltraLight Print & Copy provides authentication for printing and copying
- YSoft SAFEQ Terminal UltraLight Print Only provides authentication for printing

TECHNICAL DATA

TERMINAL ULTRALIGHT, PRINT & COPY



TERMINAL ULTRALIGHT, PRINT ONLY



| | |
|-----------------------------|------------------------------|
| Terminal power supply input | 12V DC |
| Maximum current input | 1A |
| Working temperature | +5°C to +35°C |
| Storage temperature | 0°C to +50°C |
| Working air humidity | 20% to 80% non-condensing |
| Storage air humidity | 8% to 85% non-condensing |
| Network interface | 2x 10/100 Mbit |
| RAM | 64kB |
| Flash memory | 512kB |
| Processor | Freescale Coldfire version 2 |
| Dimensions | 134mm x 74mm x 41mm |
| Weight | 170g |

ADDITIONAL TECHNICAL DATA

| MODEL DESCRIPTION | RFID FREQUENCY | CERTIFICATIONS |
|---|-------------------|--|
| YSoft SAFEQ Terminal UltraLight, Print & Copy, COTAG | 134kHz | EAC |
| YSoft SAFEQ Terminal UltraLight, Print & Copy, Cable for ext. reader (Wiegand, RS232) | N/A | EAC EU |
| YSoft SAFEQ Terminal UltraLight, Print & Copy, Indala UIN | 125kHz | EAC |
| YSoft SAFEQ Terminal UltraLight, Print & Copy, Unique | 125kHz | EAC |
| YSoft SAFEQ Terminal UltraLight, Print & Copy, Inside Contactless | 13.56MHz | EAC |
| YSoft SAFEQ Terminal UltraLight, Print & Copy, LEGIC Advant v3 | 13.56MHz / 125kHz | EAC |
| YSoft SAFEQ Terminal Ultralight Print & Copy, LF | 125kHz | EAC USA Canada |
| YSoft SAFEQ Terminal UltraLight, Print & Copy, MF+ | 13.56MHz / 125kHz | EAC EU USA Australia New Zealand Canada Malaysia Singapore UK Japan |
| YSoft SAFEQ Terminal UltraLight, Print & Copy, TIRIS 134 kHz | 134kHz | EAC |
| YSoft SAFEQ Terminal UltraLight, Print & Copy, MULTI ISO | 13.56MHz | EAC |
| YSoft SAFEQ Terminal UltraLight, Print Only, COTAG | 134kHz | EAC |
| YSoft SAFEQ Terminal UltraLight, Print Only, Cable for ext. reader (Wiegand, RS232) | N/A | EAC EU |
| YSoft SAFEQ Terminal UltraLight, Print Only, Indala UIN | 125kHz | EAC |
| YSoft SAFEQ Terminal UltraLight, Print Only, Unique | 125kHz | EAC |
| YSoft SAFEQ Terminal UltraLight, Print Only, Inside Contactless | 13.56MHz | EAC |
| YSoft SAFEQ Terminal UltraLight, Print Only, LEGIC Advant v3 | 13.56MHz / 125kHz | EAC |
| YSoft SAFEQ Terminal UltraLight, Print Only, LF | 125kHz | EAC USA Canada |
| YSoft SAFEQ Terminal UltraLight, Print Only, MF+ | 13.56MHz / 125kHz | EAC USA Canada |
| YSoft SAFEQ Terminal UltraLight, Print Only, TIRIS 134 kHz | 134kHz | EAC |
| YSoft SAFEQ Terminal UltraLight, Print Only, MULTI ISO | 13.56MHz | EAC |

© 2021 Y Soft Corporation, a.s. All rights reserved. Y Soft, YSoft SAFEQ, and YSoft SAFEQ Terminal UltraLight are trademarks and/or registered trademarks of Y Soft Corporation in the European Union and/or individual countries. All other trademarks and/or registered trademarks are the property of their respective owners. P/N UltraLight-DS-10-2021